

CHARTRE DES COURANTS POUR TRANSFORMATEURS TRIPHASÉS ET MONOPHASÉS

Transformateurs triphasés

KVA	208	240	347	380	480	600
6.0	16.7	14.4	10.0	9.1	7.2	5.8
10.0	27.8	24.1	16.6	15.2	12.0	9.6
15.0	41.6	36.1	25.0	22.8	18.0	14.4
22.0	61.1	52.9	36.6	33.4	26.5	21.2
30.0	83.3	72.2	49.9	45.6	36.1	28.9
45.0	124.9	108.3	74.9	68.4	54.1	43.3
50.0	138.8	120.3	83.2	76.0	60.1	48.1
75.0	208.2	180.4	124.8	114.0	90.2	72.2
112.5	312.3	270.6	187.2	170.9	135.3	108.3
150.0	416.4	360.9	249.6	227.9	180.4	144.3
225.0	624.6	541.3	374.4	341.9	270.6	216.5
300.0	832.7	721.7	422.2	455.8	360.9	288.7

Transformateurs monophasés

KVA	120	208	240	347	480	600
3.0	25.0	14.5	12.5	8.6	6.3	5.0
5.0	41.7	24.0	20.8	14.4	10.4	8.3
7.5	62.5	36.1	31.3	21.6	15.6	12.5
10.0	83.3	48.1	41.7	28.8	20.8	16.7
15.0	125.0	75.1	62.5	43.2	31.3	25.0
25.0	208.3	120.2	104.2	72.0	52.1	41.7
37.5	312.5	180.3	156.3	108.1	78.1	62.5
50.0	416.7	240.4	208.3	144.1	102.4	83.3
75.0	625.0	360.6	312.5	216.1	156.2	125.0
100.0	833.3	480.8	416.3	288.2	208.3	166.7
150.0	1250.0	721.2	625.0	432.3	312.5	250.0
200.0	1666.7	961.5	833.3	576.4	416.7	333.3

